

# FR4060 Akame

Fixed Mount Barcode Scanner



## Features

- ◆ **Quick to switch mode.**  
The Scan Mode Switch at the top of the scanner allows users to swiftly toggle between the Regular and Screen modes.
- ◆ **Superior motion tolerance.**  
Exceptional motion tolerance (2.5m/s) and large FOV (46°) enhance user experience.
- ◆ **IP50 rated sealing.**  
An IP50-rated seal renders the scanner impervious to dust, water and other contaminant.
- ◆ **Superb reading performance.**  
Armed with Newland's fifth-generation of UIMG technology, the FR4060 is capable of reading 1D as well as high-volume 2D barcodes on the screen covered with protective film.
- ◆ **1.2m drop resistance.**  
The scanner withstands multiple 1.2m drops to concrete (six sides, one drop per side).
- ◆ **IR trigger.**  
The IR sensor in the scanner enables speedy capture of barcodes presented to it, markedly increasing throughput and productivity.

## Application Scenarios

POS, customer service desk, ticket validators, O2O.

# FR4060 Akame

## Fixed Mount Barcode Scanner

<b>Performance</b>	Image Sensor		CMOS	
	Pixels		752*480 CMOS	
	Symbologies	2D		PDF417, QR Code, Data Matrix, Chinese Sensible Code, etc.
		1D		EAN-13, EAN-8, UPC-A, UPC-E, ISSN, ISBN, Codabar, Code 128, Code 93, ITF-6, ITF-14, Interleaved 2 of 5, Industrial 2 of 5, Standard 2 of 5, Matrix 2 of 5, GS1 Databar, Code 39, Code 11, MSI-Plessey, Plessey, etc.
	Resolution		≥5mil	
	Motion Tolerance		2.5m/s	
	Scan Angle	Pitch		±60°@ 0°Roll and 0° Skew
		Roll		±360°@ 0°Pitch and 0° Skew
		Skew		±55°@ 0°Roll and 0° Pitch
	Symbol Contrast		≥25%	
	Interface		RS-232, USB	
	<b>Physical</b>	Dimensions (L×W×H)		83×81×148mm
Weight			292g	
Notification			Beep, LED indicator	
Current		Operating		150mA
		Standby		120mA
<b>Environmental</b>	Operating Temperature		-20°C~50°C	
	Storage Temperature		-40°C~70°C	
	Humidity		5%~95% (non-condensing)	
	ESD		±14 kV (air discharge), ±8 kV (direct discharge)	
	Drop		1.2m drops to concrete (for six sides, one drop per side)	
	Sealing		IP50	
<b>Certifications</b>			FCC Part15 Class B , CE EMC Class B	
<b>Accessories</b>	Cable	USB	Used to connect the FR40 to a host device.	
		RS-232	Equipped with a power connector; used to connect the FR40 to a host device.	
	Power Adaptor		Used to provide power for the FR40. Output: DC5V, 1.5A; Input: AC100~240V, 50~60Hz	

\*Specifications are subject to change without notice.\*

Version: V1.0

**Newland EMEA**  
+31 (0) 345 87 00 33  
info@newland-id.com

**Newland D-A-CH**  
+49 (0) 294 298 76758  
info@newland-id.de

**Newland UK**  
+44 (0) 1442 212 020  
sales@newland-id.co.uk

**Newland Nordic & Baltic**  
+46 (0) 708 847 767  
nordic@newland-id.com

**Newland Ibérica**  
+34 (0) 93 303 74 66  
info@newland-id.es

**Newland France**  
+31 (0) 345 87 00 33  
france@newland-id.com

**Newland Middle East**  
+31 (0) 345 87 00 33  
middleeast@newland-id.com

**Newland South Africa**  
+27 (0) 11 553 8010  
info@newland-id.co.za

**Newland Italy**  
+39 (0) 342 056 2227  
italy@newland-id.com

**Newland Russia**  
+31 (0) 345 87 00 33  
russia@newland-id.com